

1 6 UMT sublayer

2 6.2 Receive path specification

3 6.2.1 Ingress tunnel exit rules

4 6.2.1.1 Ingress tunnel exit rule for OAM subtype

6 6.2.1.2 Ingress tunnel exit rule for L2 subtype

7 The tunnel exit rule for the L2 subtype is shown in Table 6-5. This rule converts an UMT PDU into a L2
8 frame. The conversion is straight-forward and involves only a replacement of the destination MAC address
9 value and the Ethertype value.

10 **Table 6-5—Ingress tunnel exit rule for L2 subtype**

Conditions	Actions
1. ETYPE_LEN == UMT_TYPE 2. DA == <local_MAC_addr> 3. UMT_SUBTYPE == L2_subtype	1. CHANGE(DA, L2DestAddr) 2. CHANGE (SA, L2SrcAddr) 3. CHANGE(ETYPE_LEN, L2LengthType))
NOTE: L2_subtype – Ethertype value identifying UMT PDUs (see 5.1) <local_MAC_addr> - MAC address associated with the given port L2DestAddr, L2SrcAddr, L2LengthType – UMT PDU fields, as defined in 5.2.4.	

14