

Table 13-26—Return codes

Code	Name	Description
0x80	No Error	The operation was successfully completed.
0x81	Too Long	Length of result exceeded eOAMPDU data field available.
0x86	Bad Parameters	Parameters for the requested <u>attribute or</u> action fail error checking.
0x87	No Resources	The device does not currently have the resources (table entries, memory, etc.) to perform the requested action.
0x88	System Busy	The device is not currently in the proper state to perform the requested action.
0xA0	Undetermined Error	Unknown or unlisted attribute error.
0xA1	Unsupported <u>Attribute/Action</u>	An <u>The requested attribute or action requested</u> is not supported on this device, <u>i.e., the branch and/or the leaf values are not recognized or are undefined under the supplied context.</u>
0xA2	May Be Corrupted	The value of an attribute counter may be invalid due to reset.
0xA3	Hardware Failure	An attribute hardware error prevented the operation from completing.
0xA4	Overflow	The requested attribute experienced overflow error.
<u>0xA5</u>	<u>Invalid Context Object</u>	<u>The supplied object context is not recognized (i.e., an unknown leaf value under the branch 0xDA “Identification”) or the ObjectInstance value is out of range for the given device.</u>